





Probe Specifications

Mechanical

Full Travel: .110 (2.79)
Recommended Travel: .060 (1.52)
Mechanical Life Exceeds: 250 x10° cycles

Operating Temperature: -55°C to +85°C Consult factory for other temperature requirements.

Electrical (Static Conditions) 5 amps d.c. max Maximum Current Rating (Non-inductive DC) Average Probe Resistance 30 mΩ

Materials and Finishes

Plunger:

Hard nickel over beryllium copper, gold plated

Barrel: Gold plated Hard nickel over

brass

Spring: Standard:

Alternate:

Beryllium copper, silver plated Music wire

Mounting Hole Size:

.043 (1.09) min

Spring Force in Spring Type	oz. (grams) Preload	Recommended Travel
Standard Alternate	0.40 (11.35) 1.0 (28.38)	1.14 (32.35) 3.0 (85.13)
Tip Styles	В	
Termination		

UNLESS OTHERWISE SPECIFIED:
DIMENSIONS ARE IN INCHES
TOLERANCES ARE:
.X=±.06 ANGLES=±2*
.XX=±.03
.XXX=±.005
.XXXX=±.0005
TAPER ON ANY DIA. .002/IN MAX

ALL CORNER RADII .002 MAX

Applications

EMULATION probes are used in battery charger or electronic device applications such as:

- 1. Camcorders
- 2. Circuit board to board docking stations
- 3. Cellular phones
- 4. 2-way radios
- 5. Computer docking stations
- 6. Cordless phones
- 7. Chargers
- 8. InkJet Printers
- 9. Notebook and laptop computers
- 10. AC/DC power supplies

Benefits and Features

- 1. Low resistance (average 16 milliohms)
- 2. Better contact than nickel-plated strip contacts
- 3. Maintains high compliancy
- 4. Less susceptible to damage
- 5. Can accomodate up to .025" subsurface battery mating contact
- Longer life than conventional interconnects

Notes: Consult factory for higher temperature applications

LENGTH 12.98mm PLUNGER D
PITCH 2.65mm (SINGLE PLUNGER)

ALL DIMENSIONS ARE IN INCHES UNLESS OTHERWISE SPECIFIED



Emulation Technology, Inc.

-VLSI and SMT ADAPTERS and ACCESSORIES-

759 FLYNN ROAD, CAMARILLO, CA 93012

TEL: (805)383-8480 FAX:(805)383-8484

SHEET: 1 OF 1 O4/19/06 REVISION: B ASSEMBLY DRAWING

CHECKED: DRAWN: K.BURNS DESCRIPTION: POGO-PIN-13.0-2

DO NOT SCALE DRAWING POGO-PIN-13.0-2